


Flush-mounting axial auxiliary module with one command. An axial push-buttons on the front; this product can be used in combination with the auxiliary wired inputs of the following devices of the Chorusmart range: connected commands, connected 1- channel On/Off actuator, connected movement sensors, EVO commands, or as a wired command for a connected 2-channel ZigBee interface. The module with 1 auxiliary axial command can also be used to directly command small resistive or weakly inductive loads such as ringers and buzzers (max. 10VA);. The device must be completed with one of the front buttons key available.

Descriere	1-channel auxiliary axial command	Sursă de alimentare	100 ÷ 240 V ac - 50/60 Hz
Nr. module	2	Nr. canale în intrare	-
Local control	Via front push button (to complete with button key)	Auxiliary input channel voltage	-
Temperatură de stocare	-25 ÷ +70 °C	N. canali ingresso LED	1
Temperatură de funcționare	-5 ÷ +45 °C	Tensione canali ingressi LED	100 ÷ 240 V ac - 50/60 Hz
Relative humidity (non-condensative)	Max 93%	Nr. canale în ieșire	1
Front light signaling	Led albastru	Contacte de ieșire	1A (AC1)
Terminale de cablare	Cu șuruburi	240 V ac Incandescent-halogen lamps	-
Capacitate strângere terminal cabluri flexibile (mm²)	Max. 1,5	240 V ac LED lamps	-
Capacitate strângere terminal cabluri rigide (mm²)	Max. 1,5	Loads piloted from electronic transformers 240 V ac	-
Context	Interno, luoghi asciutti	240 V Fluorescent lamps	-
Clasă de protecție IP	IP20 (with button key)	Load control	-
Standard	2014/35/EU (LVD), 2011/65/EU + 2015/863 (RoHS), EN 60669-1, EN IEC 63000		

DIMENSIONAL



TECHNICAL SYMBOLOGY

IP

IP20 (with button key)

STANDARDS/APPROVALS



GEWISS S.p.A. Via A. Volta, 1
24069 Cenate Sotto - Bergamo - Italy
tel. +39 035 94 61 11 fax +39 035 94 69 09

www.gewiss.com
sat@gewiss.com
Last update 31/03/2023

Data, measures, designs and pictures are shown only as informative purposes, and could be changed without previous notice